




### FX 90



	L	P	H
FX 90/24	630/24.6	315/12.3	590/23
FX 90/50	755/29.5	320/12.5	695/27.2


CE



Type	Volt/Hz	Cod.	Lt.	dB (A)	LWA	Grup./Pump	Cil./St.	/lmin	C.F.M.	m <sup>3</sup> /h	bar	psi	HP	kW	Watt	min-1	Kg	m <sup>3</sup>
FX 90/24	230/50/1Δ	1160020000	24	70	95	GM 192	1/1	190	6,7	11,4	8	116	1,5	1,1	1300	2850	28	0.099
FX 90/50	230/50/1Δ	1166010000	50	71	95	GM 192	1/1	190	6,7	11,4	8	116	1,5	1,1	1300	2850	50	0.180



### COSMOS



	L	P	H
COSMOS 24	630/24.6	310/12	580/22.6
COSMOS 40	630/24.6	320/12.5	695/27.2
COSMOS 50	755/29.5	320/12.5	695/27.2


CE



Type	Volt/Hz	Cod.	Lt.	dB (A)	LWA	Grup./Pump	Cil./St.	/lmin	C.F.M.	m <sup>3</sup> /h	bar	psi	HP	kW	Watt	min-1	Kg	m <sup>3</sup>
COSMOS 24	230/50/1Δ	1160040000	24	70	95	GM 193	1/1	240	8,5	14,4	8	116	2	1,5	1700	2850	30	0.099
COSMOS 40	230/50/1Δ	1161510000	40	71	95	GM 193	1/1	240	8,5	14,4	8	116	2	1,5	1700	2850	45	0.150
COSMOS 50	230/50/1Δ	1168010000	50	71	95	GM 193	1/1	240	8,5	14,4	8	116	2	1,5	1700	2850	52	0.180



### SUPERCOSMOS



	L	P	H
SUPERCOSMOS 24	630/24.6	310/12	580/22.6
SUPERCOSMOS 40	630/24.6	320/12.5	695/27.2
SUPERCOSMOS 100	1200/47	400/15.8	850/33.2

CE



Type	Volt/Hz	Cod.	Lt.	dB (A)	LWA	Grup./Pump	Cil./St.	/lmin	C.F.M.	m <sup>3</sup> /h	bar	psi	HP	kW	Watt	min-1	Kg	m <sup>3</sup>
SUPERCOSMOS 24	230/50/1Δ	1160050000	24	72	95	GM 244	1/1	250	8,8	15	8	116	2,5	1,8	1850	2850	30	0.099
SUPERCOSMOS 40	230/50/1Δ	1161500000	40	73	95	GM 244	1/1	250	8,8	15	8	116	2,5	1,8	1850	2850	45	0.150
SUPERCOSMOS 100	230/50/1Δ	1169500000	100	73	95	GM 244	1/1	250	8,8	15	8	116	2,5	1,8	1850	2850	63	0.409